

ERROR & CAUTION CODES

E 0	Normal Operating Condition
E 1	Reverse Polarity (hot [black] and neutral [white] wires reversed)
E 2	Open Ground (no ground [green, copper] wire connection)
E 3	Line 1 High Voltage (line voltage above 132V)
E 4	Line 1 Low Voltage (line voltage below 104V)
E 5	Line 2 High Voltage (line voltage above 132V) PT50X models only
E 6	Line 2 Low Voltage (line voltage below 104V) PT50X models only

Report ALL above codes [**E0**–**E6**] to Campground Manager.
Progressive Tech Support CANNOT help with these issues.

E 7	Line Frequency High (line frequency above 69Hz)
E 8	Line Frequency Low (line frequency below 51Hz)
E 9	Data Link Down
E10	Replace Surge Protector Module

Contact Progressive Industries Tech Support
for [**E7**–**10**] Error Codes.